# DATA SHEET

Valid from: 17.09.2018 ED-PB-90–FC



PROFIBUS bus connector, Sub-D with Fast Connect, Cable outlet 90°, integrated terminating resistor, with 12 Mbit/s

### **Approvals**

21700502







### **Technical data**

Cable outlet: 90°

Connection type: Fast Connect

Programming-/Diagnosis-interface: No

For cable type: Solid conductor (versions with "S" at the cover)

Solid conductor/ 7-/ 19-wires (version from 01.07.2015, identifiable

with the missing "S")

For outer cable diameter: 5.0 to 8.0 mm

Degree of protection: IP20 Pollution degree: 2

Dimensions: 72 x 40 x 17 mm (LxWxH)

Terminating resistor:  $150 \Omega$ , integrated, connectable via slide switch Interfaces: PROFIBUS- participant: Sub-D socket, 9-pins PROFIBUS-cable: FC standard cable,  $\emptyset$  0.64 mm

Transmission rate: Max. 12 Mbit/s

Supply voltage: 4.75 to 5.25 V DC (from terminal)

Current consumption: Max. 12.5 mA Operating temperature: -25 °C to +70 °C

\*The maximum ambient temperature for UL is + 60 °C

Transport- and storage temperature:  $-25\,^{\circ}\text{C}$  to  $+80\,^{\circ}\text{C}$  Relative humidity: Max. 75 % at  $+25\,^{\circ}\text{C}$  Material, housing: Metallized housing

Fixture screw: 4-40 UNC
Norms/approvals: IEC 61158
IEC 61784

UL-File E331560


ETIM 5.0 Class-ID: EC001132

Creator: PAMA7 Document: DB21700502EN Version: 03 Page 1 of 2

21700502	DATA SHEET	& LADD
Valid from: 17.09.2018	ED-PB-90-FC	<b>WLAPP</b>

## Description

When used in the middle of a PROFIBUS network (two cable connections, node) the switch at the connector must be in the 'OFF' position. If used as a terminating connector (one cable connection, segment end), the switch must be in the 'ON' position. If the switch is in the 'ON' position the outbound bus cable is disconnected.



### **Application range**

Automation, industrial machinery and plant engineering

### Note

Photographs are not true to scale and do not represent detailed images of the respective products.

Creator: PAMA7	Document: DB21700502EN	Page 2 of 2
Released: IVSE1/PDP	Version: 03	rage 2 or 2